FX0296 Datasheet



Product Name // Fuseholder FX0296 Range Protection Category PC1 Panel Mount Solder Tag Termination 5mm x 20mm Fuse Screw Cap Carrier Hand Release





nage not found or type unknown

// Product Description:

- 0 Protection Category PC1 Fuseholder
- 5mm x 20mm fuse carrier, Screw Cap
- 0 Choice of cap size and release method, depending on part code:
- 0 FX0296 - standard cap, Hand Release
- 0 FX0296/S - standard cap, Screwdriver Release
- O FX0296/1 large cap, Hand Release
- O Panel mount
- 0 Solder Tag Termination
- 0 Insulation Boot for rear of connector available separately (part code 9820)

// General Information:

Product Display Title: Product Family:

Product Series:

Body Material: Current Max:

Flamability Rating:

Function:

Fuseholder Protection Category:

Fuse Carrier:

Max Operating Temperature: Min Operating Temperature:

Voltage Max:

Protection Category PC1 Fuseholder

Fuseholders

PC Mounting PC1, PC2 and PC3

Nylon 66 - Glass Filled

6.3A

UL94V-0

Pc1 Fuseholder

PC1

Screw Cap/Hand Release

5mm x 20mm +85°C

-20°C

250V

// Product PDF Links

Fuseholders product data

// Product 3D CAD Model Links



FX02963D CAD Model