
## FX0415/S Datasheet



Product Name // Fuseholder FX0415-FX0416 Series Protection Category PC2 Panel Mount 4.8 Series Tab Termination 6.3mm x 32mm Fuse Screw Cap Carrier Screwdriver Release







## // Product Description:

- O Protection Category PC2 Touchproof Fuseholder
- O Screw Cap fuse carrier
- O Choice of fuse size and release method, depending on part code:
- FX0415 6.3mm x 32mm fuse, Hand Release
- O FX0415/S 6.3mm x 32mm fuse, Screwdriver Release
- O FX0416 6.3mm x 25mm fuse, Hand Release
- O FX0416/S 6.3mm x 25mm fuse, Screwdriver Release
- Panel mount
- Q 4.8 Series Tab Termination
- O Insulation Boot for rear of connector available separately (part code 12932)

## // General Information:

Product Display Title:

Product Series:

Approvals:

Body Material:

Current Max:

Flamability Rating:

Function:

Fuseholder Protection Category:

Fuse Carrier:

Fuse Size:

Max Operating Temperature: Min Operating Temperature:

Voltage Max:

Protection Category PC2 Touchproof Fuseholder

Fuseholders

PC Mounting PC1, PC2 and PC3

UL

Nylon 66 - Glass Filled

16A

UL94V-0 Pc2 Fuseholder

PC2

Screw Cap/Screwdriver Release

6.3mm x 32mm

+85°C

-20°C

250V

## // Product PDF Links



// Product 3D CAD Model Links



FX0415/S3D CAD Model