FX0458/2 Datasheet



Product Name // Fuseholder FX0458 Series Protection **Category PC2 Snap Fit To Panel Solder Tag Termination** 2mm-3mm Panel 5mm x 20mm Fuse Screw Cap Carrier **Screwdriver Release**





nage not found or type unknown

// Product Description:

- O Protection Category PC2 Touchproof Fuseholder
- 5mm x 20mm fuse carrier, Screw Cap, Screwdriver Release
- Snap Fit To Panel mount, choice of panel thickness depending on part code: /1 - 1mm-1.5mm (black sleeve), /2 - 2mm-3mm (grey sleeve)
- O Solder Tag Termination
- O Insulation Boot for rear of connector available separately (part code 11327)

// General Information:

Product Display Title: Product Family:

Product Series:

Approvals:

Body Material:

Current Max:

Flamability Rating:

Fuseholder Protection Category: Fuse Carrier:

Fuse Size:

Max Operating Temperature: Min Operating Temperature: Max Panel Thickness:

Min Panel Thickness:

Voltage Max:

Protection Category PC2 Touchproof Fuseholder

Fuseholders

PC Mounting PC1, PC2 and PC3

CSA, UL

Polyester (PET)

10A, 16A UL94V-0

Pc2 Fuseholder

PC2

Screw Cap/Screwdriver Release

5mm x 20mm

+85°C

-20°C 3mm

2mm

250V

// Product PDF Links

Fuseholders product data

// Product 3D CAD Model Links



FX0458/23D CAD Model